

# Zener Barrier

## MTL7728+



### Features

- ▶ Simple installation onto standard DIN raiting
- ▶ Removable colour-coded terminals for easy connection, accommodate conductors up to 2.5mm<sup>2</sup>
- ▶ Supports one zone for I.S. products
- ▶ Input circuitry protected against reverse polarity
- ▶ Can be used with the IFD-E(IS) industrial IR<sup>3</sup> flame detector (two barriers per IFD)

### Description

Model MTL7728+ is an intrinsically safe, zone-powered, Zener-diode barrier for use in conventional fire detection systems for protection within hazardous areas.

The single zone contains two stages of pulse-tested Zener or forward- connected diodes and an 'infallible' terminating resistor. In the event of an electrical fault in the safe area, the diodes limit the voltage that can reach the hazardous area and the resistor limits the current. A fuse protects the diodes, and the two stages of voltage limitation ensure continued safety if either stage should fail. No active output-current limiting circuits are employed.

Model MTL7728+ is certified 'ia' for all zones and 'IIC' for all explosive atmospheres.

**PLEASE NOTE: The Earth connections to the unit are made via connection to the DIN rail (this product MUST be earthed).**

Specification	
Ordering Code	MTL7728+
Maximum voltage of Zener diode when fuse blows	28V
Minimum value of terminating resistor	300Ω
Maximum short-circuit current	93mA
Number of Channels	1
Maximum end-to-end resistance	333Ω
Working Voltage	25.9V
Maximum Voltage	26.5V
Fuse Rating (continuous)	50mA
Operating Temperature Range	-20°C to + 60°C (continuous working)
Storage Temperature Range	-40°C to + 80°C
Maximum Humidity	95%RH - Non Condensing (at 40°C)
Weight (g) / Dimensions (mm)	140 / H90 x W105 x D12.6
Mounting Method	DX070 Box

**FURTHER INFORMATION:** [www.mtl-inst.com](http://www.mtl-inst.com)

Hochiki Europe (UK) Ltd. reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Hochiki Europe (UK) Ltd. to be a complete and up-to-date description.