



Product Information

Date: *October 6, 2011*

Product: MG6250 (2-Partition 64-Zone Wireless Console with GPRS/GSM)

Subject: New hardware revision, PCB#900-3003-000
New firmware release, V1.20

Web links: To go to the MG6250 product page, [click here](#)

Important Note: Please note that firmware V1.20 is only compatible with hardware revision PCB#900-3003-000.

New Features: Universal LCD support

The MG6250 now comes equipped with a new LCD screen that supports any language, with the exception of Chinese and Arabic. The previous LCD only supported a limited character set.

SMS text message support

It is now possible to arm in regular, stay, or sleep mode, and disarm your system by sending an SMS text message from a cell phone. The message must be sent to the MG6250's phone number, as determined by the cell phone network provider. The text message command has a specific format and specific elements that must be sent to the phone number of the MG6250 console.

*Please note in order for the MG6250 console to receive SMS text messages a GPRS14 module with an activated SIM card must be installed.

The format is as follows:

C[USER CODE].[ACTION].A[PARTITIONS].[PHONE NUMBER]

Action commands:

| | |
|-------------|---------|
| Regular arm | [ARM] |
| Stay arm | [STAY] |
| Sleep arm | [SLEEP] |
| Disarm | [OFF] |

Arm/disarm examples:

| | |
|--------------------------|--------------------------|
| Regular arm partition#1 | C1234.ARM.A1.5145551234 |
| Stay arm partition#2 | C1234.STAY.A2.5145551234 |
| Disarm partition#1 and 2 | C1234.OFF.A3.5145551234 |

The following table provides a list of all additional SMS commands supported.

| | |
|---|-----------------------------|
| P[password].A.[IP address].P[port number] | Initiate GPRS remote access |
| P[password].IP.[call back phone number] or C[user code].IP.[call back phone number] | Obtain IP address of GPRS14 |
| P[password].RESET | Reset the GPRS14 |
| P[password].STATUS | Obtain GSM/GPRS programming |



Contact: If you require any additional information or if you have any questions, please do not hesitate to contact our support department.

Email: support@paradox.com

Fax: 450.491.2313

Phone: 1.800.791.1919 (N. America)

00.1.450.491.7444 (International)

Paradox Security Systems LTD – Product Information #MG6250-011-10-06